



## BY-M4C

Cardoid Lavalier Microphone

### Cardioid Polar Pattern

The lavalier mic with the cardioid pattern yields a generous pickup area while maintaining adequate feedback and noise rejection at the off-axis section of the capsule.

### Specification:

Type	Electret Condenser Microphone
Frequency Response	35-18KHz +/-3dB
	120 dB
Sensitivity	-38dB +/-3dB / 0dB=1V/Pa, 1kHz
Output Impedance	200 ohms
Power Requirement	48V Phantom Power
Signal-to-Noise Ratio	78 dB
Accessories	Windscreen, Lapel clip

### BOYA AUDIO EQUIPMENT (SHENZHEN) CO., LIMITED

Add: A16 building, New Material Industrial Park of Silicon Valley Power, Guanlan Town, Shenzhen, China

Tel: (86)0755-28435910

Email: sales@boya-mic.com

---

2014 BOYA inc. Visit us on the web at [www.BOYA-mic.com](http://www.BOYA-mic.com)