



BY-M8C

Professional Cardioid Lavalier Microphone

Cardioid Polar Pattern

The lavalier mic with the cardioid pattern yields a generous pickup area while maintaining adequate feedback and noise rejection at the off-axis section of the capsule.

Features:

- Professional Clip-On Mic for Camcorders, Audio recorders etc.
- Cardioid condenser microphone
- Broadcast-Quality condenser mic
- XLR output connector
- All durable brass body
- Includes lapel clip, foam windscreen, pouch

Specifications

Type	Electret Condenser	Power Requirement	48V Phantom Power
Capsule diameter	12.0mm (0.47")	Signal-to-Noise Ratio	80 dB
Polar Pattern	Cardioid	Output Connector	3-pin XLR
Frequency Response	35-18KHz +/-3dB	Accessories	Windscreen, lapel clip, pouch
Maximum Sound Input Level	120 dB	Length	Connector: 10cm (3.9") Cable: 2m (6.6')
Sensitivity	-38dB +/-3dB / 0dB=1V/Pa, 1kHz	Weight	111g (3.9oz)
Output Impedance	200 ohms		

2015 BOYA inc. Visit us on the web at www.BOYA-mic.com